

3 dBi Dipole Portable Antenna 2400-2500/4900-7125 MHz SMA Connector

FM51RD1025

Features

- · Tilt and Swivel Design
- · 2.4 GHz, 5 GHz, 6 GHz and 7 GHz Bands

Applications

- · Infotainment Systems, Routers, WiFi Hotspots, HD Video Transmission, Gateways, Dash Cameras, Public Transportation
- WiFi 6e (802.11ax) Networks

- · SMA Plug (Male) Connector
- 2.5 to 3.5 dBi Gain
- · Connected Cars or Self-Driving Cars, Fleet Management, Logistics
- · IoT, Cellular, Zigbee, Z-Wave, Bluetooth

Description

The FM51RD1025 Fairview Microwave WiFi 6e Rubber Duck Antenna is a high performance, compact designed for 2.4, 5, 6 and 7 GHz bands. This tilt and swivel rubber duck antenna is available to ship the same day. It features a SMA Plug (Male) Connector. The FM51RD1025 can be used on all enterprise or commercial radios and access points that have SMA female connections. This SMA Male rubber duck antenna is suitable for WiFi Hotspots (IEEE 802.11ax/ac/n/b/g) as well as IoT, Bluetooth, and Zigbe.

The high performance Fairview Microwave FM51RD1025 has 3 dBi of gain and broad coverage. This WiFi 6e 2400 to 7125 MHz rubber duck antenna is in stock and available to ship the same day. Contact our knowledgeable sales and technical support teams for your answers on any Fairview Microwave products.

1/2

Configuration

Design Portable Band Type Single

Radiation Pattern Omni Directional

Wavelength Polarization Vertical Connector Type SMA Male

Housing Material and Plating ABS, Black

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	2,400		7,125	MHz
Input VSWR		1.4:1	1.7:1	
Impedance		50		Ohms
Gain	2.6	3		

Mechanical Specifications

Housing Material **ABS** Housing Plating/Color Black

Size

Lenath 0.8 in [20.32 mm] Width 0.8 in [20.32 mm] Height 5.3 in [134.62 mm] Weight 0.76 lbs [344.73 g]



3 dBi Dipole Portable Antenna 2400-2500/4900-7125 MHz SMA Connector

FM51RD1025

Environmental Specifications

Temperature

Operating Range

-30 to +65 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Typical Radiation Pattern

Appendix

Electrical Downtilt: Angle in the antenna's elevation pattern in which the maximum gain occurs.

Gain: Antenna's average gain.

Front to Back Ratio @ 180°±30°: Average difference between the antenna's maximum gain and the maximum gain in the antenna's back lobe over ±30° angles.

Cross-polarization Ratio (dB): Typical difference between the co-polarization and cross-polarization gain across the sector's 3 dB Beam Width.

Dedicated to serving the needs of the Wireless Internet Service Provider (WISP) market, KP Performance Antennas offers purpose built products that reliably perform in the field. KP Performance Antennas product line consists of Yagi, Grid, Omni, Dish and other style antennas that operate in the 900 MHz, 2.4 GHz, 3 GHz, and 5 GHz frequencies.

3 dBi Dipole Portable Antenna 2400-2500/4900-7125 MHz SMA Connector from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 3 dBi Dipole Portable Antenna 2400-2500/4900-7125 MHz SMA Connector FM51RD1025

URL: https://www.fairviewmicrowave.com/single-antenna-2.4-2.5-ghz-3-dbi-gain-sma-fm51rd1025-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

