

# **FMCA9968 DATA SHEET**

## **RA SMPS Female to SMA Female Cable FM-P047HF** Coax

The RA SMPS female to SMA female cable using FM-P047HF coax, part number FMCA9968, from Fairview Microwave is in-stock and ships same day. This Fairview SMPS to SMA cable assembly has a female to female gender configuration with 50 ohm flexible FM-P047HF coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA9968 SMPS female to SMA female cable assembly operates to 18 GHz. The right angle SMPS interface on the FM-P047HF cable allows for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

Description	Min	Т	ур	Max	U	nits
Frequency Range	DC			18	(	GHz
VSWR				1.4:1		
Velocity of Propagation		7	70			%
RF Shielding	90					dB
Capacitance		29 [95.14] pF/ft		[pF/m]		

**Specifications by Frequency** 

Dart Number	art Number Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
Part Number		Frequency	1000	2000	4500	9000	18000	MHz	weight (bs)
FMCA9968	Custom Lengths	Insertion Loss (Typ.)	0.35	0.49	0.763	1.107	1.681	dB/ft	
FIVICASSOS	Available	ilisertion Loss (Typ.)	1.15	1.61	2.51	3.64	5.52	dB/m	
FMCA9968-6	6 inch	Insertion Loss (Typ.)	0.4	0.52	1.29	1.02	1.45	dB	0.009
FMCA9968-12	12 inch	Insertion Loss (Typ.)	0.57	0.76	1.67	1.57	2.3	dB	0.011
FMCA9968-18	18 inch	Insertion Loss (Typ.)	0.75	1.01	2.05	2.13	3.14	dB	0.013

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

0.12\*SORT(FGHz) dB Loss due to Connector 1: Loss due to Connector 2: 0.1 dB Base Weight: 0.011 pounds Additional Weight per Inch: 0.00033 pounds

#### **Mechanical Specifications**

#### **Cable Assembly**

Weight 0.0089 lbs [4.04 g]

#### Cable

Cable Type **Impedance** Inner Conductor Type Inner Conductor Material and Plating Dielectric Type Number of Shields Shield Layer 1 Shield Layer 2

FM-P047HF 50 Ohms

Solid Copper, Silver

PTFE 2

Silver Plated Copper Tape Silver Plated Copper Braid



## **Configuration:**

- SMPS Female Right Angle
- SMA Female
- FM-P047HF


## Features:

- Max Frequency 18 GHz
- Shielding Effectivity > 90 dB
- 70% Phase Velocity
- Double Shielded
- FEP Jacket

## **Applications:**

- General Purpose
- Laboratory Use
- Scientific research
- High-reliability, high-density for aerospace & defense application
- Ground base station & communication systems, avionics, radar systems

## Cable Diagram:



Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Jacket Material FEP, Blue

Jacket Diameter 0.06 in [1.52 mm]

Repeated Minimum Bend Radius 0.1 in [2.54 mm]

#### **Connectors**

Description	Connector 1	Connector 2				
Туре	SMPS Female Push-on	SMA Female Threaded				
Specification		MIL-STD-348				
Impedance	50 Ohms	50 Ohms				
Contact Material & Plating	Beryllium Copper, Gold	Beryllium Copper, Gold				
Contact Plating Spec.	50 µin minimum	MIL-G-45204				
Dielectric Type	PTFE	PTFE				
Outer Cond Material & Plati	ng Beryllium Copper, Gold	Brass, Gold				
Outer Cond Plating Spec.	50 µin minimum	MIL-G-45204				
Body Material & Plating	Beryllium Copper, Gold	Brass, Gold				
Body Plating Spec.	30 µin minimum	MIL-G-45204				

**Environmental Specifications** 

Temperature

Operating Range -55 to +165 deg C

**Compliance Certifications** (see product page for current document)

**Plotted and Other Data** 

Notes:

**How to Order** 

Part Number Configuration:

Example: FMCA9968-12 = 12 inches long cable

FMCA9968-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020

REV 1.0 Page 2 of 4





RA SMPS Female to SMA Female Cable FM-P047HF Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA SMPS Female to SMA Female Cable FM-P047HF Coax FMCA9968

URL: https://www.fairviewmicrowave.com/ra-smps-female-to-sma-female-cable-fm-p047hf-coax-fmca9968-p.aspx



301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





