

SM2389 DATA SHEET

10-32 Female (Jack) to 10-32 Female (Jack) Adapter, Nickel Plated Brass Body, 1.2 VSWR

10-32 female to 10-32 female adapter part number SM2389 from Fairview Microwave is in-stock and ships same day. This Fairview 10-32 to 10-32 adapter has a female to female gender configuration. SM2389 10-32 female to 10-32 female adapter operates to 2 GHz. The Fairview Microwave RF adapter provides excellent VSWR of 1.2:1 maximum.

RF adapters can be used to enable connections between two connector types that would otherwise not mate. Certain RF adapter configurations can also be used to protect connectors on expensive equipment where the number of connect and disconnect cycles is high. An RF, microwave, or millimeter wave adapter is connected to the equipment and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Fairview Microwave also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	DC		2	GHz
VSWR			1.2:1	

Electrical Specification Notes: Values at 25°C, sea level

Mechanical Specifications

S	İ	Z	е

 Length
 0.336 in [8.5 mm]

 Width
 0.25 in [6.35 mm]

 Weight
 0.0065 lbs [2.95 g]

Description	Connector 1	Connector 2
Туре	10-32 Female	10-32 Female
Polarity	Standard	Standard
Interface Specification	MIL-C-39012	MIL-C-39012
Hex Size	1/4 inch	



Configuration:

- 10-32 Female Connector 1
- 10-32 Female Connector 2
- 50 Ohm
- Straight Body Geometry

Features:

- VSWR of 1.2:1 max up to 2 GHz
- 10-32 interface meets MIL-C-39012
- Contact plating according to MIL-G-45204
- Gold Plated Beryllium Copper Contact

Applications:

General Purpose Test

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Material Specifications

Description	Connector 1	Connector 2	
Туре	10-32 Female	10-32 Female	
Contact Material	Beryllium Copper	Beryllium Copper	
Contact Plating	Gold	Gold	
Contact Plating Spec.	MIL-G-45204	MIL-G-45204	
Insulation Material	PTFE	PTFE	
Outer Contact Material	Brass	Brass	
Outer Contact Plating	Nickel	Nickel	
Outer Contact Plating Spec.	QQ-N-290	QQ-N-290	
Body Material	Brass	Brass	
Body Plating	Nickel	Nickel	
Gasket Material	Silicone Rubber	Silicone Rubber	

Environmental Specifications

Temperature

Operating Range

-65 to +165 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

10-32 Female (Jack) to 10-32 Female (Jack) Adapter, Nickel Plated Brass Body, 1.2 VSWR from Fairview Microwave is instock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 10-32 Female (Jack) to 10-32 Female (Jack) Adapter, Nickel Plated Brass Body, 1.2 VSWR SM2389

URL: https://www.fairviewmicrowave.com/10-32-female-10-32-female-adapter-sm2389-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020

REV 1.1 Page 2 of 3





